Important Safety Instructions
• Turn off all power to the Junction Box before making any electrical adjustments.
• Always disconnect the power before installing/replacing bulbs, during cleaning or maintenance.
• To avoid the risk of fire, do not exceed the recommended wattage.
• Consult a qualified, licensed electrician before installation.

To Assemble
1. Install the beveled mounting disc to the J-box using the supplied mounting screw hardware (2X).

2. Screw in the bulb. *Do not over-tighten the bulb.*

3. Slide the shade (2x) onto the main body and align the holes on the shades to those in the main body. Screw in the thumb screw (3x) for each shade to secure them properly.

4. Hold the ceiling plate near the installed mounting disc, and using the supplied lever nuts, connect the wires from the fixture to those in the J-box.

5. Loosen each set screw (3X) at the 120° position on the Flush Mount ceiling plate.

6. Push the ceiling plate over the mounting disc, flush with the ceiling, and tighten each set screw (3X).

7. Turn on the power to confirm you have made good wire connections.

Care Instructions
• Wipe with a soft cloth. Do not use chemical cleaner.

Mounting Screw (2x)
Mounting Disc
Set Screw (3x)
Ceiling Plate
Thumb Screw (6x)
Bulb
Shade (2x)
Main Body

*We recommend installation by a licensed electrician

Electrical:1 x E26 12W LED Bulb Only