

Installation Instructions

Chartier 10 Light Circular Chandelier

Important Safety Instructions

- Turn off all power to the Junction Box before making any electrical adjustments.
- Always disconnect the power before installing/replacing bulbs, during cleaning or maintenance.
- To avoid the risk of fire, do not exceed the recommended wattage.
- Consult a qualified, licensed electrician before installation.

To Assemble

1. Attach the mounting disc to the J-box using the supplied mounting screw hardware (2X) and hang the canopy using the carabiners (2X).
2. Additional holes are added to the mounting disc to allow for extra mounting screw hardware (not provided), depending on various ceiling constructions. Anchors or ceiling blocking strongly advised.
3. Connect the wires from the chandelier to those from the J-Box using the Wago wire connectors.
4. Push the ceiling plate over the mounting disc, flush with the ceiling and tighten the set screws (3X) using the supplied allen key.
5. Gently squeeze the shade bracket to allow the bracket to pass through the interior of the shade until the foot of the bracket is below the crystal.
DO NOT LET GO OF THE SHADE UNTIL THE BULB IS INSTALLED
6. Slide the shade up along the cord and screw in the bulbs (10X).
DO NOT OVER TIGHTEN THE BULBS
7. Slide the shade down into place. Ensure the bracket ledge sits beneath the shade to securely hold it in place.
8. Turn on the power and check that good connections have been made.

Do not leave the crystal hanging without the bulb installed at any given time. When changing the bulb, make sure to hold the crystal, so it can not fall.

Care Instructions

- Wipe with a soft cloth. Do not use chemical cleaner.

