## **Important Safety Instructions**

- Turn off all power to the Junction Box before making any electrical adjustments.
- Always disconnect the power before installing/replacing bulbs, during cleaning or maintenance.
- To avoid the risk of fire, do not exceed the recommended wattage.
- Consult a qualified, licensed electrician before installation.

## To Assemble

- 1. Install both beveled mounting discs to the ceiling, one over a J-box, using the supplied mounting screw hardware (2X).
- 2. Feed the electrical wires through one of the Drop Rods while inserting the threaded connectors (2X) and Drop Rods (2X) into the Main Body.
- 3. Insert the threaded connectors (2X) into the Drop Rods and through the Ceiling Plate.
- 4. Fasten each nut and washer (2X) over the threaded connectors to secure the fixture to the ceiling plate.
- 5. Hold the chandelier near the ceiling and connect the wires from the chandelier to those in the J-Box using the supplied wire nuts.
- 6. Push the Ceiling Plates over the Mounting Discs flush with the ceiling and tighten all 6 set screws.
- 7. Screw all 12 bulbs into the sockets. \*DO NOT OVERTIGHTEN THE BULBS\*. Place all 12 shades over the bulbs.
- 8. Turn on the power to confirm good connections.

## **Care Instructions**

• Wipe with a soft cloth. Do not use a chemical cleaner.

